

MuxLab Dante/Quad Channel Audio PoE Gateway

4 in / 4 out, PoE

Tuotekoodi:	500765
EAN:	627699007655
Valmistaja:	MuxLab
%t_warranty%:	24



MuxLab 500765 Dante/Quad Channel Audio PoE Gateway permits non-Dante compatible analog audio equipment to interface with Dante compatible professional audio equipment.

The unit allows Dual two-channel or Quad single-channel full range (20Hz to 20KHz) balanced analog audio signals to be transmitted over the network to Dante compatible professional audio equipment. Dual two-channel or Quad single-channel balanced analog audio signals may also be received from Dante compatible equipment in the same manner. The unit may be connected via Cat5e/6 cable up to 100m from an Ethernet Switch.

The Dante/Quad Channel Audio PoE Gateway includes four single-channel balanced analog audio-in and four single-channel balanced analog audio-out ports, via phoenix connectors. The Quad single-channel balanced analog audio-in ports may be connected to line level balanced analog audio signals or to line level balanced microphones. The Quad single-channel balanced analog audio-out ports may be connected to balanced analog audio amplifiers supporting line level inputs, such as the MuxLab 500217 Audio Zone Amplifier 100W, or to two pairs of powered speakers for direct sound output.

- Interface analog audio equipment to Dante audio equipment
- Supports Dual two-channel or Quad single-channel full range balanced analog audio from 20Hz to 20KHz
- Transmission up to 100m over Cat5e/6
- Supports Quad single-channel balanced analog audio-in and Quad single-channel balanced analog audio-out from Dante audio equipment.
- Balanced audio ports may be interfaced to unbalanced audio ports when only 2 of 3 pins are used per channel
- IP managed for remote control
- Controllable via the Audinate Dante Controller software
- PoE powered